

# Large LED Up/ Down Counter



## MODEL TYPES

- L106SUDC-110-6-4 6" > Production Counter, Counts Up or Down
- L106SUDC-110-8-4 8" > Production Counter, Counts Up or Down

## FEATURES

- > High Brightness LED display with four digits
- > Displays real-time production information to your employees
- > Will up-count or down-count by 1 when a customer-supplied on/off switch is activated
- > Terminal block to wire in 3 customer supplied contacts, count up, count down and reset
- > Momentary switch will preset the unit to a value designated on 4 Thumbwheel switches on the end cap
- > Remote keypad with 10' of cable included to preset display
- > Mounting bracket included
- > On-board power supply for photo-eye, push button, etc, input
- > Factory service One-year Warranty on parts and labor
- > 6' power cord
- > NEMA 1

- ELECTRONIC SPECIFICATIONS:
- > Power Source 120VAC @ 60Hz
  - > Power Consumption Max. 15 Watts
  - > Current Draw 500-800 mA
  - > Watts
  - > Current Draw 1.0-3.0 amps

## ACCESSORIES AND OPTIONS

- > Optional control box with 10' of cable for run and reset
- > Optional battery backup for time memory upon loss of power
- > Relay output to activate an alarm, light, etc. when unit reaches preset value
- > Optional RS232/RS485 for serial output

## ORDERING INFORMATION

Model Type	> L106SUDC
Voltage	> 110V
Number Height	> 2", 4", 6", 8"
Number of Digits	> 4
Timing Option	> M=MM:SS, H=HH:MM
Ordering Example	> Part Number for 6" L106SUDC-110-6-4
	> Part Number for 8" L106SUDC-110-8-4

Also available in 2.3" ( L106SUDC-110-4-2 ) and 4" ( L106SUDC-110-4-4 ) Numbers